

# AP 22

Engine : Perkins  
 Alternator : Mecc Alte  
 Control System : P 602



## ISO8528

This generator set has been designed to meet ISO 8528 regulation.

## SZUTEST

This generator set is manufactured in facilities certified to ISO 9001.



This generator set is available with CE certification.

## 2000/14/EC

Enclosed product is tested according to EU noise legislation 2000/14/EC

### 3 Phase Ratings, 50 Hz, PF 0,0

Voltage	Standby Rating (ESP)		Prime Rating (PRP)		
	kVA	kw	kVA	kw	Amp
400/230	22,00	17,60	20,00	16,00	28,90

**Standby Rating (ESP):** Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. ESP is in accordance with ISO 8528. Overload is not allowed.

**Prime Rating (PRP):** Applicable for supplying power to varying electrical load for unlimited hours. PRP is in accordance with ISO 8528. 10 % overload capability is available for a period of 1 hour within 12-hour period of operation, in accordance with ISO 3046.

### STANDARD SPECIFICATIONS

- Water cooled, Diesel engine
- Radiator with mechanical fan
- Protective grille for rotating and hot parts
- Electric starter and charge alternator
- Starting battery (with lead acid) including rack and cables
- Engine coolant heater
- Base frame design incorporates an integral fuel tank and anti-vibration isolators
- Flexible fuel connection hoses
- Single bearing, class H alternator
- Industrial exhaust silencer and steel bellows supplied separately (for open sets)
- Static battery charger
- Manual for application and installation

### OPTIONAL EQUIPMENTS

#### ENGINE

- Remote Radiator Cooling

#### ALTERNATOR

- Main line circuit breaker

#### CONTROL SYSTEM

- Remote annunciator panel
- Remote relay output
- Alarm output relays
- Remote communication with modem
- Earth fault, single set
- Charge Ammeter

#### OTHER ACCESSORIES

- Automatic or manual fuel filling system
- Manual oil drain pump
- Residential silencer
- Enclosure: weater protective or sound attenuated
- Duct adapter ( on radiator)
- Inlet and outlet motorised louvers
- Inlet and outlet acoustic baffles
- Trailer
- Tool kit for maintenance
- Supplied with oil and coolant - 30 °C
- Battery isolating switch
- Main Fuel Tank

#### TRANSFER SWITCH

- Three or four pole contactor
- Three or four pole motor operated circuit breaker

# AP 22

Engine : Perkins  
 Alternator : Mecc Alte  
 Control System : P 602

## ➤ DIESEL ENGINE SPECIFICATIONS

Manufacturer		Perkins
Model		404A-22G1
No. of Cylinders and Build		4 Cylinder, In Line
Aspiration and Cooling		Naturally Aspirated
Maximum Standby Power		1500 rpm
		20,60 kw [27,60HP]
Total Displacement	L	2,216
Bore and Stroke	mm	84x100
Compression Ratio		23.3:1
Rated Speed (rpm)	rpm	1500
Governor		Mechanical
Oil Capacity	L	10,60
Coolant Capacity	L	7,00
Start System		12 V d.c.
Fuel Consumption	Load	%100
	L/h	5,30

## ➤ ALTERNATOR SPECIFICATIONS

Make		Mecc Alte
Model		ECP28 M/4
Frequency	Hz	50
Power	kVA	20,00
Design		Brushless, 4 poles
Phase		3
Voltage	V	400/230
Current	A	28,90
Insulation Class		H
Stator		2 / 3 steps
Rotor		Single Bearing System, Flexible Disc
Excitation System		Electronic ( AVR )

## ➤ DIEMENSIONS AND WEIGHT

Open Type	Dry Weight	Lenght	Width	Height	Tank Capacity
	kg.	mm.	mm.	mm.	L
AP 22		1361,00	850,00	1041,00	38,00
Canopy	Dry Weight	Lenght	Width	Height	Tank Capacity
	kg.	mm.	mm.	mm.	L
AK 11	615	1955	910	1171	38

# AP 22

Engine : Perkins  
 Alternator : Mecc Alte  
 Control System : P 602

## 1 P 602 - Control System



- 1 A U]b'gHh g'X]gd'Um'
- 2 8]gd'UmgVc''Vi Hrcb''
- 3 DU[ Yf]bZcfa U]jcb'Vi Hrcb''
- 4 7 ca a cb U'Ufa ]bX]W]rcf''
- 5 GHh g'@98fj''
- 6 C dYfU]jcb'gY'YV]b[ 'Vi Hrcbg''

## 2 Devices

8G9ža cXY''\$\$'5i hc' A U]bg: U]i fy V'ebfc''a cXi 'Y''  
 6UHYfmVUf[ Yf]jodi h%, !&\* ( 'j c'hžci rdi h''&+ž' 'j ) '5'f&( 'j E'cf%' ž 'j c'h) 5'f&J ž  
 9a Yf[ YbVhrcd' di g\ 'Vi Hrcb'UbX ž gYg'Z'fV'ebfc''V]fV ]rg''

## 3 Construction and Finish

7 ca dcbYbrj ]bgfU'YX' ]b'g\YYgh'Y'YbWcgi fy''D\cgd\UHY'WYa ]W'ždfY!V'U]b[ 'cZghY' 'dfcj ]Xyg V'ffcg]cb  
 fyg]ghbhgi fZJW''Dc'mYghY'V'ca dcm]Y' dck XYf'rcdV'U]hZcfa g\ ] [ 'cgg'UbX'Yi HYa Y'mXi fUV'Y ž]b]g''@cV]UV'Y  
 UbX\]b[ YX'dUbY'Xccf' d'fcj ]Xyg YUgmUWV'gg'hc' 'V'ca dcbYbrj''

## 4 Installation

7 cblfc' d'UbY' ]g'a ci bHYX'cb VUgYZUa Y k ]h' ghY' 'ghUbX''@cW]HYX' Uhi'Y' f[ \ h]g]XY' cZ'HY [ YbYfU]rcf' gyHfK \Yb'nci  
 'cc\_ Uhi'Y; Yb''GYH'Z'ca '5'HYfbU]rcf'

## 5 Generating Set Control Unit

H\Y''8G9''\$\$' ]g'U'ghUbXUfX V'ebfc''a cXi 'Y'Z'f'ci f [ YbYfU]rcf'gYhg'i d'hc' &\$\$\_J 5'UbX'ih\Ug'VYYb'XYg][ bYX'hc  
 ghUfhUbX'ghcd'X]YgY' UbX' [ Ug[ YbYfU]rcf'gYhg''H\Y'8G9''\$\$' a cXi 'Y\Ug'VYYb'XYg][ bYX'hc' a cb]rcf [ YbYfU]rcf  
 ZYei YbV'žj c'ž'W'fYb'ž'Yb[ ]bY'c' ]dfYggi fyZ'V'c'UbhiYa dYfUhi fy' fi bb]b[ \ci fg'UbX' VU]HY'fmj c'lg''A cXi 'Y  
 a cb]rcf'g' h'Y' a U]bg'gi dd'imUbX'gk ]W' c] Yf'hc' h'Y' [ YbYfU]rcf'k \Yb' h'Y' a U]bg'dck Yf'Z] ]g''H\Y'8G9''\$\$' U'gc  
 ]bX]W]Yg'cdYfU]jcbU' ghUhi g'UbX'Z]i 'hV'ebX]j]cbgž'5i hca U]hW' 'mg\i H]b[ 'Xck b' h'Y; Yb''GYhUbX' [ ] ]b[ 'Hfi Y'Z]fghi d  
 ž]i 'hV'ebX]j]cb'cZ; Yb''GYhZ]i' fy''H\Y'@78'X]gd'Um]bX]W]HYg'h'Y'Z]i 'H'

### Standard Specifications

A ]W'cd'fc'W'ggcf'V'ebfc''YX''  
 @78'X]gd'Uma U\_Yg' ]bZcfa U]jcb'YUgmhc'fYUX''  
 (!' ]bYž'\*( '1' % & d] ]Y'X]gd'Um'

# AP 22

Engine : Perkins  
 Alternator : Mecc Alte  
 Control System : P 602

## Instruments

9B: #9  
 9b[ ]bY'gdYYX"  
 C]'dfYggi fY"  
 7cc'UbhY'a dYfUhi fY"  
 F i b' hja Y"  
 6UHYfmj c'rg"  
 7cbZ[ i fUV'Y hja ]b[ "  
 ; 9B9F 5HCF  
 J c' hU[ Y f@ @B' "  
 7i ffYbhf@ @& @' "  
 : fYei YbVW"  
 A 5-BG  
 J c' hU[ Y f@ @B' "  
 : fYei YbVW"  
 A U]bg'fYUXn"  
 A U]bg'YbUV'YX"  
 ; Yb"GYhfYUXn"  
 ; Yb"GYhYbUV'YX"

## Protection Circuits

K 5F B-B;  
 7\Uf[Y Z]i fY"  
 6UHYfm@ck #:[ \ ] c' hU[ Y"  
 : U] h' ghcd"  
 @ck #:[ \ ] [ YbYfUhc'f j c' hU[ Y"  
 I bXYf#j Yf [ YbYfUhc'f ZYei YbVW"  
 Cj Yf# bXYf'gdYYX"  
 @ck c]'dfYggi fY"  
 <][ \ V'c'UbhY'a dYfUhi fY"  
 G<I H8CK BG  
 : U] h' ghUf"  
 9a Yf [ YbVW'ghcd"  
 @ck c]'dfYggi fY"  
 <][ \ V'c'UbhY'a dYfUhi fY"  
 Cj Yf# bXYf'gdYYX"  
 I bXYf#j Yf [ YbYfUhc'f ZYei YbVW"  
 I bXYf#j Yf [ YbYfUhc'f c' hU[ Y"  
 C]'dfYggi fY'gYbgcf'cdYb"  
 7cc'UbhY'a dYfUhi fY'gYbgcf'cdYb"  
 9@97 HF =75@HF #  
 ; YbYfUhc'f c' j YfW ffYbH"

## Options

: 'YI J'Y'gYbgcf'Wb VY V'c'UbhY'a dYfUhi fY'Z  
 dfYggi fY'Z dYfVW'bH [ Y f'k Ufb]b[ #]i f'Xck b# 'YVW'VW' f'f'dL  
 @c'W'gYh]b[ 'dUfUa YHfg'UbX'a cb]h'f]b[ 'Zca 'D7 h'  
 V'c'UbhY'a cXi 'Y'k ]h' I G6 V'c'UbhY'a cb'fa Ul '\* 'a H'

## Standards

9'YVW'VW' GUZYhm#9A 7 'V'a dUfV']hm6G'9B '\* \$-) \$  
 9'YVW'VW' Vi g]bYgg'Yei ]da YbH  
 6G'9B '\*%\$!\*&9A 7 'ja a i b]mighUbXUfX"  
 6G'9B '\*%\$!\*( '9A 7 Ya ]gg]cb'ghUbXUfX

## Static Battery Charger

'6UHYfmVUf [ Yf ]g'a Ubi ZVW' fYX'k ]h' gk ]h'W]b[ !a cXY'UbX'GA 8 'YVW'bc'c[ mUbX'ih\Ug\ ] [ \ YZ]VYbVW' 6UHYfmVUf [ Yf  
 a cXY'gfci hdi hJ !=VUfUW'f]gh]W]g'j YfmV'cgY'hc'gei UfY'UbX'ci hdi h]g' ]'Ua dYfz% z' ]'Zcf'%&j'c'hUbX'&+Z' ]'Zcf'&'( ]'  
 #bdi h% , ' !&\* ( j c'h57 "'Dfc]bY'&(\$) \Ug'Z' mci hdi hg\chV'VW]hdfchV'W]cb'UbX'ihVWb'VY' i gYX'Ug'U'VW'ffYbhgci fVW"  
 Dfc]bY'&(\$) #&(\$) V'Uf [ Yf\Ug\ ] [ \ YZ]VYbVW'cb[ " ]Z'Z'ck ZU]i fY'fUfY'Z' ] [ \ hk Y] [ \ hUbX'ck \YUhfUX]UfYX' ]b  
 UVW'cfXUbW'k ]h' ]'bYUf'U'fYbUf]j Yg' H\Y'V'Uf [ Yf ]g'Z]h'YX'k ]h' U'dfchV'W]cb'X]cXY'UV'cgg'h'Y'ci hdi h'7 cbbYVW'VUf [ Y'Z]  
 fY'UmV'c] VYh'YYb'dcg]h]j Y'ci hdi hUbX'7: 'ci hdi h' H\Y'mUfY'Yei ]ddYX'k ]h' F: =Z]h'f'hc'fYXi V'Y'YVW'VW'bc]gY'fUX]UfYX  
 Zca 'h'Y'XY'jVW"; Uj Ub]W' m]gc'UfYX' ]bdi hUbX'ci hdi h]m]VW'm(\_J 'Zcf\ ] [ \ fY' ]UV] ]m'

# AP 22

Engine : Perkins  
 Alternator : Mecc Alte  
 Control System : P 602

## AK 11 - Canopy



- 1 Steel structures
- 2 Emergency stop push button
- 3 Control panel is right side of the set.
- 4 Corrosion-resistant locks and hinges
- 5 Sump drains valves
- 6 Sound proof foam material
- 7 Base frame -tank

## Introduction

Sound-attenuated and Weather-protective Enclosures Sound-attenuated and weather protective enclosures for generating sets from Akxa, meet even the sound requirements and provide optimum protection from inclement weather and development by our specialist acoustic engineers. Our modular designed sound insulated canopies provide ease of access for servicing and general maintenance and interchangeable components permitting on-site repair. Enclosures are designed to optimize genset cooling performance, providing you with confidence that genset ratings and ambient capability.

## Standard Specifications

- Compact footprint, low profile design.
- Enclosure, generator set, exhaust system and fuel tank are pre-assembled, pre-integrated and shipped as one package
- Body made from steel components treated with polyester powder coating
- Fire retardant foam insulation
- Easy access to all service points
- Exhaust system inside canopy
- Large doors on each side
- Control panel viewing window in a access door
- Emergency stop push button mounted on enclosure exterior
- Cooling fan and battery charging alternator fully guarded
- Fuel fill and battery can only be reached via access doors.
- Lifting points on the base frame
- Customer options available to meet your applications needs.
- Akxa makes its generating sets' noise level tests in accordance with directive 2000/14/EC validation of the noise level test has been approved by the notified body Szutest

Width	mm.	910
Lenght	mm.	1955
Height	mm.	1171
Fuel Tank Capacity	L	38